

Falls der Mirror vom ARCH nicht funktioniert

Ich hatte das Problem, das der Update Prozesse nicht funktionierte.

```
# pacman -Syu
```



```

Pi-KVM
Welcome to Pi-KVM - Open Source IP-KVM based on Raspberry Pi

The root filesystem of Pi-KVM is mounted in read-only mode by default.
Use command "rw" to remount it in the RW-mode and "ro" to switch it back.

To prevent kernel messages from printing to the terminal use "dmesg -n 1".

To change KVM password use command "kvmd-httpsswd set admin".

Useful links:
* https://pikvm.org
* https://wiki.archlinux.org/index.php/Network_configuration

root@pikvm ~# rw
root@pikvm ~# pacman -Syu
:: Synchronizing package databases...
error: failed retrieving file 'core.db' from de3.mirror.archlinuxarm.org : The requested URL returned error: 404
error: failed to update core (failed to retrieve some files)
error: failed retrieving file 'extra.db' from de3.mirror.archlinuxarm.org : The requested URL returned error: 404
error: failed to update extra (failed to retrieve some files)
error: failed retrieving file 'community.db' from de3.mirror.archlinuxarm.org : The requested URL returned error: 404
error: failed to update community (failed to retrieve some files)
error: failed retrieving file 'alarm.db' from de3.mirror.archlinuxarm.org : The requested URL returned error: 404
error: failed to update alarm (failed to retrieve some files)
error: failed retrieving file 'aur.db' from de3.mirror.archlinuxarm.org : The requested URL returned error: 404
error: failed to update aur (failed to retrieve some files)
pikvm 18.9 KiB 0.00 B/s 00:00 [#####] 100%
error: failed to synchronize all databases
root@pikvm ~#
```

Schuld war ein per default eingetragener Mirror von ARCH linux.

Original in der /etc/pacman.d/mirrorlist ⇒ Server = [http://de3.mirror.archlinuxarm.org/\\$arch/\\$repo](http://de3.mirror.archlinuxarm.org/$arch/$repo)

die Ziffer 3 durch z.B. 5 austauschen.

Server = [http://de5.mirror.archlinuxarm.org/\\$arch/\\$repo](http://de5.mirror.archlinuxarm.org/$arch/$repo)

danach noch einmal das Update auslösen

```
rw
pacman -Syu
reboot
```

Mirror Generator

Es gibt einen [Mirror Generator](#), den man benutzen kann.

Bei der Erstellung dieses Beitrages gab es auch:

- [http://de3.mirror.archlinuxarm.org/\\$arch/\\$repo](http://de3.mirror.archlinuxarm.org/$arch/$repo)
- [http://de4.mirror.archlinuxarm.org/\\$arch/\\$repo](http://de4.mirror.archlinuxarm.org/$arch/$repo)
- [http://de5.mirror.archlinuxarm.org/\\$arch/\\$repo](http://de5.mirror.archlinuxarm.org/$arch/$repo)

From:

<https://quad.logout.de/> - **quad.logout.de**

Permanent link:

<https://quad.logout.de/pikvm:updateerrorfromarch>

Last update: **2020/10/20 10:07**

